

interface aggregate-ethernet <lag_name> family ethernet-switching native-vlan-id

The native VLANID is the ID of the default VLAN (usually vlan 1) in which the port belonged to. User can change the native VLANID for port.

Command Syntax

```
set interface aggregate-ethernet <lag_name> family ethernet-switching native-vlan-id <vlan-id>  
delete interface aggregate-ethernet <lag_name> family ethernet-switching native-vlan-id <vlan-id>
```

Parameter

- <lag> Name of LAG interface.
- <vlan_id> The native-vlan-id ,VLAN identifier to associate with untagged packets .The valid VLAN number range is 1-4094.

Example

- This example creates VLAN 3 and puts ae1 on this VLAN:

```
admin@XorPlus# set vlans vlan-id 3  
admin@XorPlus# set interface aggregate-ethernet ae1 family ethernet-switching native-vlan-id 3  
admin@XorPlus# commit
```