

# interface gigabit-ethernet <port> ether-options 802.3ad

---

Users can add a specified port to a LAG.

## Command Syntax

```
set interface gigabit-ethernet <port> ether-options 802.3ad <lag>
delete interface gigabit-ethernet <port> ether-options 802.3ad
```

## Parameter

- <port> ethernet switching port identifier,the valid ports range 1-52
- <lag> Join an aggregated Ethernet interface LAG.

NOTE:

The maximum number of member ports per LAG is platform dependent, for details see [Collection of Feature Specification of Different Platforms](#).

## Example

- This example is to add ge-1/1/3 to ae1:

```
admin@XorPlus# set interface gigabit-ethernet ge-1/1/3 ether-options 802.3ad ae1
admin@XorPlus#commit
```