

# run show igmp-snooping groups

The **run show igmp-snooping groups** command shows information about multicast group member ports which is used for Layer 2 forwarding, namely, the Layer 2 forwarding table.

## Command Syntax

**run show igmp-snooping groups** [vlan <vlan-id>]

## Parameter

Parameter	Description
<b>vlan</b> <vlan-id>	Optional. Specifies a VLAN ID. The value is an integer that ranges from 1 to 4094.

## Example

- Show the information about multicast group member ports.

```
admin@XorPlus# run show igmp-snooping groups
Vlan      Group          Port List      Type
-----
1         238.255.0.1    ge-1/1/2      Static
                ge-1/1/1      Mrouter
```