

set firewall filter sequence then action

To configure the next action for a filter sequence, use the **set firewall filter sequence then action** command in L2/L3 configuration mode.

Command Syntax

```
set firewall filter filter-name sequence number then action { discard | forward }
```

Parameters

<i>filter-name</i>	Filter name.
<i>number</i>	Filter sequence number. The range is 0-9999.
discard	Discard packets that meet all match conditions.
forward	Forward packets that meet all match conditions.

Examples

The following example configures sequence 1 and 2 of the *MyFilter* filter to forward and discard matching packets, respectively.

```
admin@Switch# set firewall filter MyFilter sequence 1 then action forward
admin@Switch# set firewall filter MyFilter sequence 2 then action discard
```